

P1913-10 (tested with lithium batteries, not DC PS)								
Battery	Prop	Volts	Amps	RPM	Watts	MPH	KPH	Pitch
HP-LVX1200-2S	APC 7 ~4SF	7.88	6	9120	47	35	56	4
@	APC 7 ~5SF	7.79	6.9	8760	54	41	67	5
@	APC 7 ~6SF	7.76	7.8	8460	60	48	77	6
@	APC 8 ~3.8SF	7.63	9.2	7920	70	28	46	3.8
@	APC 8 ~6SF	7.4	11.9	6810	88	39	62	6
@	APC 9 ~3.8SF	7.31	11.5	7170	84	26	42	3.8
@	APC 9 ~4.7SF	7.33	11.9	7140	87	32	51	4.7
@	APC 10 ~3.8SF	7.16	13.7	6030	98	22	35	3.8
@	APC 10 ~4.7SF	7.16	14.2	5940	102	26.43	42.53	4.7
@	APC 6 ~4E	8.1	4	10020	32	38	61	4
@	APC 6 ~5.5E	8.03	5.1	9570	41	50	80	5.5
@	APC 7 ~5E	7.86	6.8	8850	53	42	67	5
@	APC 8 ~4E	7.72	7.9	8340	61	32	51	4
@	APC 8 ~6E	7.56	10.3	7440	78	42.27	68	6
Battery	Propeller	Volts	Amps	RPM	Watts	MPH	KPH	Pitch
HP-LVX1200-3S	APC 7 ~4SF	10.99	10.3	11190	113	42	68	4
@	APC 7 ~5SF	10.76	11.4	11130	123	53	85	5
@	APC 7 ~6SF	10.63	12.5	10560	133	60	97	6
@	APC 8 ~3.8SF	10.4	14.5	9690	151	34.86	56.09	3.8
@	APC 6 ~5.5E	10.81	7.8	12330	84	64	103	5.5
@	APC 7 ~5E	10.47	10.4	11010	109	52	84	5
@	APC 8 ~4E	10.2	12	10140	123	38	62	4
@	APC 8 ~6E	10.09	15.3	9030	155	51.3	82.54	6